



MFC-L2710DW Compact 4-in-1 mono laser printer



The MFC-L2710DW is ideal for the busy home and small office. This simple to use and easy to setup device, provides professional quality prints, together with built-in wired and wireless connectivity for printing from mobile phones and tablets.



Key features:

- Fast print speeds of up to 30 pages per minute
- Automatic 2-sided print
- 250 sheet paper input
- 50 sheet Auto Document Feeder
- Built in wired and wireless connectivity
- Up to 700 page* in-box toner
- 64MB memory

Performance designed for businesses of tomorrow

Successor to the BLI Pick Award winning 'MFC-L2700DW', the MFC-L2710DW is designed to be set-up and ready to be used in minutes. Compact, and desktop friendly. You can enjoy fast print speeds up to 30 pages per minute, and a large 50 sheet automatic document feeder, for multi-page copying and scanning. Easily share documents, by scanning and sending directly via email, or save to SharePoint and other destinations.

Maximum value for money

The wireless MFC-L2710DW, comes with a host of cost saving elements, including, automatic 2-sided printing, and high yield toner cartridges reduces the cost of each printjob.

Quiet without compromise

Print quietly without comprising on speed or quality, operating at the lowest decibel in class (under 50dB). This desktop friendly printer, can sit on your desk, printing quietly at full speed in the background, while you work.

Designed to go the distance

Built to perform for longer. The MFC-L2710DW, has been designed with you in mind. Made from robust and hardwearing materials and supported by outstanding service as standard, providing the peace of mind that your printer will keep on going.



General	Technology Electrophotographi c Laser Printer Laser Classification Class 1 Laser Product (IEC60825- 1:2014)	Processor 600MHz Memory 64MB Wired Network Interface 10Base-T/100Base-TX	Wireless Network IEEE 802.11b/g/n Control Panel 2 Line, 16 character LCD Display Local Interface Hi-Speed USB 2.0
Print	 Print Speed Standard (A4) Up to 30ppm (pages per minute) Print Speed 2-Sided (A4) Up to 15 sides per minute (8 sheets per minute) Resolution Up to 1,200 x 1,200dpi Quiet Mode A mode to reduce the printing noise by reducing the print speed to 13ppm 	Automatic 2-Sided Printing Print on to both sides of the paper FPOT (First Print Out Time) Less than 8.5 seconds from ready mode Warm Up Time Less than 9 seconds from sleep mode Print Languages GDI	
Printer Functions	N-up Printing ³ Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16) Watermark Printing ⁴ Watermark your documents with predefined text or with your own user-defined messages	Booklet Printing ^₄ Print documents in A5 booklet format using automatic or manual 2-sided print	

Printer Driver

Windows® Windows®10 (32 & 64 bit editions) Windows[®]8 (32 & 64 bit editions) Windows®7 (32 & 64 bit editions) Windows® Server 2016 (32 & 64 bit editions)* Windows® Server 2012, 2012R2 & 2008R2* Windows® Server 2008 (32 & 64 bit editions)*

Macintosh⁵ macOS 10.8.x or greater

Linux⁵ CUPS, LPD/LPRng (32 & 64 bit editions)

> * Windows[®] Server supports network printing only

1 Approx declared yield value in accordance with ISO/IEC 19752.

2 Calculated with 80g/m² paper.

3 Windows® & Mac® only.

4 Windows®only.

6 Optional download.
6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products.
For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

7 Requires Brother software.

Standard Paper Handling	Paper Input ² Standard Tray - 250 sheets Manual feed slot - 1 sheet	Automatic Document Feeder (ADF) – 50 Sheets	Paper Output ² Face Down - 120 sheets Face Up (Straight Paper Path) - 1 sheet
Media Specification	Media Types & Weights Standard Plain & recycled paper (between 60 - 163g/m ²) Manual feed slot Plain, Recycled, Bond, Label, Envelope, (between 60 - 230g/m ²) 2-sided Print Plain & recycled paper (between 60 - 105g/m ²)	Envelope & Label Printing Yes, from the Manual feel slot: support for 1 envelope / sheet	Media Sizes Standard Tray A4, Letter, A5, A5 (Long Edge), A6, Executive Manual feed slot Width: 76.2mm to 215.9mm x Length: 127mm to 355.6mm 2-sided Print A4
Mobile / Web Based Printing & Scanning	Brother iPrint&Scan (Android/ iPad / iPhone / iPod/ Windows® Phone/ 8,10 & RT) Print from, scan to, preview copie and check the machine status fro a mobile/ tablet/ laptop device Google Cloud Print 2.0 Print most common file types from any Google Cloud Print enabled application	Brother Print Service Plugin	

Сору

Speed - (A4) Up to 30cpm (copies per minute)

FCOT (First Copy Time Out) Less than 10 seconds from ready mode

Resolution Up to 600 x 600dpi

1 Approx declared yield value in accordance with ISO/IEC 19752. 2 Calculated with 80g/m² paper.

3 Windows® & Mac® only. 4 Windows® only.

5 Optional download.6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products.For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

7 Requires Brother software.

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother

Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

Scan

Scanner Type CIS (Contact Image Sensor)

Colour & Mono Scanning Yes

Scan Speed Mono 23.6ipm (images per minute)

Scan Speed Colour 7.5ipm (images per minute)

Scan Resolution from ADF Up to 600 x 600dpi

Scan Resolution from Scanner Glass Up to 1,200 x 1,200dpi Interpolated Scan Resolution Up to 19,200 x 19,200dpi

Standard Functions⁷ Scan to E-mail, OCR, Image & File Scan Features Remove Background, Skip Blank Page⁴, ID Scan⁴,

1 to 2 Scan₄, Split PDF

Scan to SharePoint^{4&7} Scan documents directly into SharePoint

Windows[®] Web Services Scanning

Scan direct into Windows[®] (from Windows[®] 7 & onwards) without needing to install a scanner driver

Scanner Driver

Windows® TWAIN & WIA Windows®10 (32 & 64 bit editions) Windows®8.1 (32 & 64 bit editions) Windows®8 (32 & 64 bit editions) Macintosh⁵ TWAIN & AirPrint macOS 10.8.x or greater

Linux⁵ SANE(32 & 64 bit editions)

Fleet Management Tools BRAdmin Light^{4&5} LAN/WAN management software Embedded Web Server Web based print management software embedded onto the device

PrintSmart Solutions (optional)

PrintSmart Cost Control Monitor and control printing costs for all Brother and 3rd party devices For more information on PrintSmart Solutions visit: **www.brother.eu**

Address Book

Speed Dials 200 locations for E-mail addresses and fax numbers

1 Approx declared yield value in accordance with ISO/IEC 19752.

2 Calculated with 80g/m² paper.

3 Windows[®] & Mac[®] only.

4 Windows®only.

5 Optional download.

For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

7 Requires Brother software.

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products.

Network and Security

Wired Network Built in Ethernet 10Base-T/100Base-TX

Network Protocols TCP/IP (IPv4 and IPv6)

Wired Network Security SMTP-AUTH, SNMP v3,SSL/ TLS(SMTP,HTTP,IPP)

Wireless Network IEEE 802.11b/g/n (Infrastructure Mode / Adhoc Mode)

Wireless Set-Up Support Wi-Fi Protected Setup (WPS)

Wireless Applications Vertical Pairing

IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/IPPS, FTP Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print), SNTP Client

IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, SMTP Client, FTP Server, SNMPv1/v2c/v3, HTTP/ HTTPS server, TFTP client and server, ICMPv6, SNTP Client, Web Services (Print) E-mail Notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

E-mail Reports

Receive usage reports on a regular basis via e-mail

IP Filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

Setting Lock

Secures access to the devices control panel by locking it

Supplies

Inbox Toner 700 pages¹

Standard Yield Toner 1,200 pages¹(TN-2410)

High Yield Toner 3,000 pages¹(TN-2420) Drum (DR-2400) Approx 12,000 pages

Carton Contents Toner cartridge, drum, power supply cord, driver software for Windows®, Quick Set-Up Guide (PC interface cable NOT included) The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media.

Dimensions and Weights With Carton (WxDxH) 410 x 398.5 x 318.5 mm -11.8kg Without Carton (WxDxH) 580 x 517 x 434 mm - 14.7kg

Duty Cycles

Recommended Monthly Up to 2,000 pages monthly print volume Maximum Monthly⁶ Up to 15,000 pages monthly print volume

1 Approx declared yield value in accordance with ISO/IEC 19752.

- 2 Calculated with 80g/m² paper.
- 3 Windows® & Mac® only
- 4 Windows®only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products.
- For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

7 Requires Brother software.

Power Consumption

Printing - 440W (260W in quiet mode), Ready - 42W, Sleep - 6.2W, Deep sleep -0.6W, Off - 0.03W

TEC Value 1.232kWh / Week

Sound Pressure Level Printin g 48dbA, Quiet mode printing 44dbA, Ready Up to 30dbA

Power Saving

This enables the printer to consume less energy when not in use

Toner Saving

This reduces the toner usage and helps to reduce the total cost of printer ownership

Energy Star Yes

Eco Mode Yes

Fax Modem

33,600bps (Super G3)

PC Fax Send^{9&3} Send faxes directly from your PC

PC Fax Receive984 Receive faxes directly to your PC

Fax Forwarding

Sends a fax received in memory to another preprogrammed fax number

1 Approx declared yield value in accordance with ISO/IEC 19752.

- 2 Calculated with 80g/m² paper. 3 Windows[®] & Mac[®] only.
- 4 Windows®only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products.
- For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

7 Requires Brother software.