



# Compact 4-in-1 mono laser printer

MFC-L2752DW











F

www.brother.eu

# Compact 4-in-1 mono laser printer

The MFC-L2752DW is ideal for the busy home and small office, requiring multifunction capabilities. This quiet, compact, desktop printer boasts wired and wireless connectivity and large Auto Document Feeder supporting 2-sided print, scan and copy functionality. With the addition of NFC (Near-Field Communication), you simply 'tap and print' from your mobile phone.

MFC-L2752DW



# **Key Features:**

- Fast print speeds of up to 34 pages per minute
- Automatic 2-sided print, scan and copy
- 250 sheet paper input
- 50 sheet Auto Document Feeder
- Built in wired and wireless connectivity
- Near-Field Communication (NFC), for mobile print
- Up to 1,200 page\* inbox toner
- 6.8cm colour touchscreen
- 256MB memory

# Performance designed for businesses of tomorrow

The MFC-L2752DW is engineered to increase efficiency, with fast print speeds of up to 34 pages per minute with automatic 2-sided print, and 50 sheet automatic document feeder for automatic 2-sided copy and scan. Save time by using the print-from and scan-to popular cloud services directly from the 6.8cm touchscreen, including Dropbox, Google Drive™, Evernote, OneNote and more. Enjoy the added benefit of creating up to 12 custom shortcuts on the touchscreen for your most used features. Together with built-in NFC, you can now use your mobile phone and 'tap' to print for added ease of use.

# Maximum value for money

More pages can be printed with the large up to 1,200 page\* inbox toner, ensuring that you are ready to print, straightaway. Together with a host of feature rich functionality, ensures that your print outs are professional and cost effective.

# **Quiet without compromise**

Print quietly without comprising on speed or quality, operating at the lowest decibel in class (under 50dB). All the models throughout the range are designed to sit on your desk, printing quietly at full speed while you work without interruption.

# Designed to go the distance

Built to perform for longer. The MFC-L2752DW, has been designed with you in mind. Made from robust and hardwearing materials and supported by outstanding service as standard, providing the peace of mind that your printer will keep on going.



## General

### **Technology**

Electrophotographic Laser Printer

# **Laser Classification**

Class 1 Laser Product (IEC60825-1:2014)

# **Processor** 600MHz

Memory 256MB

# **Wired Network Interface**

10Base-T/100Base-TX

# Wireless Network

IEEE 802.11b/g/n

# **Control Panel**

6.8cm colour touchscreen

#### **Local Interface**

Hi-Speed USB 2.0

# **Shortcuts**

12

# **Print**

# **Print Speed Standard (A4)**

Up to 34ppm (pages per minute)

# Print Speed 2-Sided (A4)

Up to 16 sides per minute (8 sheets per minute)

### Resolution

Up to 1,200 x 1,200 dpi

# **Quiet Mode**

A mode to reduce the printing noise by reducing the print speed to 13ppm

# **Automatic 2-Sided Printing**

Print on to both sides of the paper

# **FPOT (First Print Out Time)**

Less than 8.5 seconds from ready mode

# Warm Up Time

Less than 9 seconds from sleep mode

# **Print Languages**

PCL6, BR-Script3 (PostScript®3™ Language Emulation), PDF version1.7

# **Embedded Fonts (PCL)**

73 scalable fonts, 12 bitmap fonts, 16 barcodes

# **Embedded Fonts (Postscript)**

66 scalable fonts

# **Embedded Barcodes (PCL)**

Code39, Interleaved 2 of 5, FIM (US-PostNet, Post Net (US-PostNet) EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN(EAN), ISBN(UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI

# **Printer Functions**

# N-up Printing<sup>3</sup>

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)

### Poster Printing<sup>4</sup>

Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages

## Watermark Printing<sup>4</sup>

Watermark your documents with predefined text or with your own user-defined messages

### ID Printing<sup>4</sup>

Add identification to your printed documents (date & time, short custom message or PC username)

### Manual 2-Sided Print<sup>4</sup>

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

# **Booklet Printing<sup>4</sup>**

Print documents in A5 booklet format using automatic or manual 2-sided print

#### Print Profiles<sup>3</sup>

Store your favourite driver settings as profiles to easily recall them

# Print Text In Black<sup>4</sup>

Converts all text in your documents to black when printed

## **Print Archive<sup>4</sup>**

An electronic carbon copy feature that saves an electronic copy of all printed documents as a PDF file

# **Printer Driver**

### Windows®

Windows® 10 (32 & 64 bit editions) Windows® 8 (32 & 64 bit editions) Windows® 7 (32 & 64 bit editions) Windows® Server 2016 (32 & 64 bit editions)\* Windows® Server 2012, 2012R2 & 2008R2\* Windows® Server 2008 (32 & 64 bit editions)\*

### Macintosh<sup>5</sup>

macOS 10.8.x or greater

# Linux<sup>5</sup>

CUPS, LPD/LPRng (32 & 64 bit editions)

# PostScript Universal Printer Driver

Driver for Windows® that enables you to print to any network or locally-connected Brother laser printer that supports PostScript

# **PCL** Driver

Generic PCL XL driver

\* Windows® Server supports network printing only

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19752.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows® & Mac® only.

<sup>4</sup> Windows® only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

<sup>7</sup> Requires Brother Software.

<sup>8</sup> Must be web connected.

# Standard Paper Handling

# Paper Input<sup>2</sup>

Standard Tray - 250 sheets Manual feed slot - 1 sheet

# Automatic Document Feeder (ADF) – 50 Sheets

# Paper Output<sup>2</sup>

Face Down - 120 sheets Face Up (Straight Paper Path) - 1 sheet

# **Media Specification**

# Media Types & Weights Standard

Plain & recycled paper (between 60 - 163g/m²)

# Manual feed slot

Plain, Recycled, Bond, Label, Envelope, (between 60 - 230g/m²)

# 2-sided Print

Plain & recycled paper (between 60 - 105g/m²)

# **Envelope & Label Printing**

Yes, from the Manual feel slot: support for 1 envelope / sheet

# Media Sizes Standard Tray

A4, Letter, A5, A5 (Long Edge), A6, Executive

# Manual feed slot

Width: 76.2mm to 215.9mm x Length: 127mm to 355.6mm 2-sided Print

# Mobile / Web Based Printing & Scanning

# Brother iPrint&Scan (Android)

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an Android device

# Brother iPrint&Scan (iPad / iPhone / iPod)

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an iPad / iPhone / iPod Touch

# Brother iPrint&Scan (Windows® Phone)

Print from and scan to a smart phone running the Windows® Phone Operating System

# Brother Print&Scan (Windows® 8,10 & RT)

Print from and scan to a Windows® 8,10 or Windows RT Tablet

# **Google Cloud Print 2.0**

Print most common file types from any Google Cloud Print enabled application

### CreativeCentre8

Download and print Brother CreativeCenter content

# Apple AirPrint

Print from and scan to most common file types from any AirPrint enabled application

# **Brother Print Service Plugin**

Print from Android devices without a dedicated App

# Mopria

Print most common file types from Mopria supported Android devices

### Web Connect<sup>8</sup>

Print from and scan to without using a PC on Box, Dropbox, Evernote, OneDrive, Google Drive™ OneNote

# Copy

# Speed - (A4)

Up to 34cpm (copies per minute)

# **FCOT (First Copy Out Time)**

Less than 10 seconds from ready mode

### Resolution

Up to 600 x 600dpi

# Multi-Copying/Stack/Sort

Makes up to 99 copies of each page / Stacks or Sorts

# Enlargement/Reduction Ratio

Reduce or Increase document sizes from 25% to 400% in 1% increments

# N in 1 Copying

Allows the user to compress 2 or 4 pages on to a single A4 sheet

# 2in1 ID Copying

Allows the user to copy both sides of an ID card to a single A4 sheet

# **Grey Scale**

256 shades of grey (8 bit)

### **Receipt Copying**

Produces clearer copies of receipts

# **Enlarge Text Copy**<sup>8</sup>

Makes reading copied documents easier if the size of the text on the original document is small

- 1 Approx declared yield value in accordance with ISO/IEC 19752.
- 2 Calculated with 80g/m² paper. 3 Windows® & Mac® only.
- 4 Windows® only.
- 5 Optional download
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.
- 7 Requires Brother Software.
- 8 Must be web connected.

# Scan

Scanner Type

Dual CIS

Colour & Mono Scanning Yes

Scan Speed Mono

22.5ipm (images per minute)

**Scan Speed Colour** 

7.5ipm (images per minute)

Scan Speed 2-Sided (A4)

Up to 22.5 mono / 7.5 colour ipm (images per minute)

**Scan Resolution from ADF** Up to 600 x 600dpi

Scan Resolution from Scanner Glass

Up to 1,200 x 1,200dpi

Interpolated Scan Resolution

Up to 19,200 x 19,200dpi

Colour Depth

16,777,216 colour variations (24 bit)

**Grey Scale** 

256 shades of grey (8 bit)

Standard Functions<sup>7</sup>

Scan to E-mail, OCR, Image, File, FTP & Network. Cloud Scanning

**Scan Features** 

Remove Background, Skip Blank Page<sup>4</sup>, ID Scan<sup>4</sup>, 1 to 2 Scan<sup>4</sup>, Split PDF Scan To Microsoft Office7

Scan to Microsoft® Word, Microsoft® Excel & Microsoft® PowerPoint

Scan to Searchable PDF

Scan documents to searchable PDF files

Scan to SharePoint<sup>4&7</sup>

Scan documents directly into SharePoint

Windows® Web Services Scanning

Scan direct into Windows® (from Windows® 7 & onwards) without needing to install a scanner driver

# Scanner Driver

Windows®

TWAIN & WIA
Windows® 10
(32 & 64 bit editions)
Windows® 8.1
(32 & 64 bit editions)
Windows® 8
(32 & 64 bit editions)

Macintosh<sup>5</sup>

TWAIN & AirPrint macOS 10.8.x or greater

Linux<sup>5</sup>

SANE (32 & 64 bit editions)

# Fleet Management Tools

Unattended Installer4

Ability to centrally deploy and customise our drivers and software

MSI Installer4

Modular installers that can be distributed through Active Directory®

**BRAdmin Light**<sup>4&5</sup>

LAN/WAN management software

**Embedded Web Server** 

Web based print management software embedded onto the device

**Driver Deployment Wizard<sup>4</sup>** 

Easily create print drivers for hassle free deployment over your network

# PrintSmart Solutions (optional)

**PrintSmart Cost Control** 

Monitor and control printing costs for all Brother and 3rd party devices

For more information on PrintSmart Solutions visit:

# **Address Book**

**Speed Dials** 

200 locations for E-mail addresses and fax numbers

Group Dial

A combination of up to 20 groups can be stored for broadcasting

- 1 Approx declared yield value in accordance with ISO/IEC 19752.
- 2 Calculated with 80g/m² paper.
- 3 Windows® & Mac® only.
- 4 Windows® only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.
- 7 Requires Brother Software.
- 8 Must be web connected.

# **Network and Security**

### **Wired Network**

Built in Ethernet 10Base-T/100Base-TX

# Wired Network Security

SMTP-AUTH, SNMP v3,SSL/ TLS(SMTP,HTTP,IPP)

# **Wireless Network**

IEEE 802.11b/g/n (Infrastructure Mode / Adhoc Mode)

# **Wireless Network Security**

SMTP-AUTH, SSL/TLS (SMTP,HTTP,IPP), SNMP v3, WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES)

# Wireless Set-Up Support

Wi-Fi Protected Setup (WPS)

# **Wireless Applications**

Vertical Pairing

# **Network Protocols**

TCP/IP (IPv4 and IPv6)

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/IPPS, FTP Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print), **SNTP Client** 

# IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, SMTP Client, FTP Server, SNMPv1/v2c/v3, HTTP/ HTTPS server, TFTP client and server, ICMPv6, SNTP Client, Web Services (Print)

#### **E-mail Notifications**

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

# **E-mail Reports**

Receive usage reports on a regular basis via e-mail

#### **IP Filter**

Restrict which network users can or cannot access the device over the network (IPv4 only)

### **Setting Lock**

Secures access to the devices control panel by locking it

# **Supplies**

# **Inbox Toner** 1,200 pages1

# **Standard Yield Toner** 1,200 pages<sup>1</sup> (TN-2411)

**High Yield Toner** 3,000 pages<sup>1</sup> (TN-2421)

# Drum (DR-2401)

Approx 12,000 pages

# **Carton Contents**

Toner cartridge, drum, power supply cord, driver software for Windows®, Quick Set-Up Guide (PC interface cable NOT included)

The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media.

# **Dimensions and** Weights

# Without Carton (WxDxH)

410 x 398.5 x 318.5 mm -12.0kg

### With Carton (WxDxH)

580 x 517 x 434 mm -15.1kg

# **Duty Cycles**

# **Recommended Monthly**

Up to 2,000 pages monthly print volume

# Maximum Monthly<sup>6</sup>

Up to 15,000 pages monthly print volume

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19752.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows® & Mac® only.

<sup>4</sup> Windows® only.

<sup>5</sup> Optional download

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

<sup>7</sup> Requires Brother Software.

<sup>8</sup> Must be web connected.

# **Environment**

# **Power Consumption**

Printing - 475W (260W in quiet mode), Ready - 42W, Sleep - 6.4W, Deep sleep - 1.1W, Off - 0.03W

### **TEC Value**

1.412kWh / Week

#### **Sound Pressure Level**

Printing 49dbA, Quiet mode printing 44dbA, Ready Up to 30dbA

### **Power Saving**

This enables the printer to consume less energy when not in use

# **Toner Saving**

This reduces the toner usage and helps to reduce the total cost of printer ownership

# **Energy Star**

Yes

# Fax

#### **Fax Modem**

33,600bps (Super G3)

### PC Fax Send9&3

Send faxes directly from your PC

#### PC Fax Receive9&4

Receive faxes directly to your PC

#### **Automatic Redial**

Automatic redialling if the recipient fax is busy

# **Telephone Index**

An electronic, alphabetical listing of stored speed dials and group numbers

# **Chain Dialling**

Allows the user to store parts for long dialling sequences in different speed dial locations

# Distinctive Ring Detection (UK & Denmark only)

An external service that allows two or more telephone numbers shared on a single fixed line and use different ring tones

# Speaker / Ring Volume

3 levels and off

# Fax / Tel Switch

Automatic recognition of fax and telephone reception

### Super Fine

Enables quality transmission of very small print and line drawings

### Contrast

Auto / light / dark

### **Enhanced Remote Activate**

Transfer a fax call, answered on an extension phone, to the fax machine

# **Delayed Timer**

Up to 50

#### Quick-Scan

Approximately 2.5 seconds per page A4 standard resolution

# **Memory Transmission**

Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)

# **Out of Paper Reception**

Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)

# **Dual Access**

Send the same fax message to up to 250 separate locations (manual 50 locations)

# **Broadcasting**

Receive usage reports on a regular basis via e-mail

### **Auto Reduction**

When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet

# **ECM**

### (Error Correction Mode)

The MFC will detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)

# **Fax Forwarding**

Sends a fax received in memory to another pre-programmed fax number

### **Remote Access**

Allows users to remotely access their machine

### Fax Retrieval

Allows remote access to faxes stored in the machine

## **Remote Maintenance**

Allows users to maintain their MFC remotely

## Remote Set-Up<sup>3</sup>

Allows users to set-up the MFC from their PC

# **Grey Scale**

256 shades (8 bit) of grey are available for faxing

# **Fax Stamp**

Add the date and time to all received faxes

# **Cover Page**

Create custom cover pages for outgoing faxes

- 1 Approx declared yield value in accordance with ISO/IEC 19752.
- 2 Calculated with 80g/m² paper.
- 3 Windows® & Mac® only.
- 4 Windows® only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.
- 7 Requires Brother Software.
- 8 Must be web connected.













# Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com

