



# Visitor badge and event pass printer

QL-820NWBcVM



CONTINUOUS ROLL



PRE-SIZED LABELS



BLUETOOTH CONNECTION



NETWORK CONNECTION



PC CONNECTION

brother.co.uk/QL820NWBcVM

# Visitor badge and event pass printer

The Brother QL-820NWBcVM visitor badge printer offers additional security by providing guests attending your business or event with an identification badge. Print visitor and event badges from your PC, Mac, smartphone or tablet using the range of connectivity options available.

QL-820NWBcVM



#### **Key Features:**

- USB, Ethernet, Wi-Fi and Bluetooth connectivity
- Adhesive label and non-adhesive card badge rolls available
- Optional rechargeable Li-ion battery base for use away from power sources
- Design and print visitor badges using Brother P-touch Editor on your PC or Mac, or by using the iPrint&Label App on your smartphone or tablet
- Can also be used with compatible third party visitor and event management apps and software

#### Versatile visitor badge printing

The Brother QL-820NWBcVM visitor badge printer offers additional security by printing badges for guests attending your business or event. Print visitor and event badges from your PC, Mac, smartphone or tablet using USB, Ethernet, Wi-Fi and Bluetooth and the free Brother badge printing software and apps. Includes 3 non-adhesive card rolls to print around 1,000 badges.

Can also be used with professional visitor management apps and software from other companies that offer compatibility for this model of badge printer.





#### Included items

Printer 3 x DK-N55224 non-adhesive card rolls (30.48 metres each)

USB cable AC power cord AC Adapter Documentation

#### **Printing / Media**

**Printing technology** 

Direct thermal

**Print resolution** 300 x 300dpi

Maximum print speed\*

110 labels per minute or 176mm per second

**Label widths** 12mm - 62mm Maximum print width

60.96mm

Minimum label length

12.7mm

Maximum label length

1 metre

Media sensor type

Reflective

Cutter

Yes (full cut / guillotine type)

Media types

DK rolls (DK pre-sized labels /

DK continuous tape)

#### **Control panel**

**Buttons** 

Power / Feed / Cut

#### Connectivity

**USB** 

USB version 2.0 full-speed

(type B)

Bluetooth

Bluetooth 5.2

**Bluetooth profiles** 

SPP (Serial Port Profile) OPP (Object Push Profile) HCRP (Hard Copy Cable

Replacement Profile)

iOS and Android compatibility

Yes (including MFi and AirPrint)

#### **Memory**

Flash (for label templates)

6MB

Locations

(for label templates)

255

#### Power

Power

220-240V AC internal power supply

Yes

### Auto sleep mode

#### **Weights / Dimensions**

**Dimensions** 

125 (w) x 234 (d) x 145 (h) mm

Weight

1.16kg

#### Software / Firmware

#### Operating system support

(visit http://support.brother.com for latest downloads and support)

#### Windows:

Vista, 7, 8, 8.1, 10, 11, Server 2008, 2008 R2, 2012, 2012 R2, 2016, 2019, 2022 Mac: 10.10, 10.11, 10.12, 10.13, 10.14, 10.15, 11, 12 iOS 6 (SDK), 7 (SDK), 8, 9 (iPrint&Label App) iOS 7, 8, 9, 10, 11 (iOS SDK) Android 4.1 or greater (iPrint&Label App) Android 4.0.3 or greater (Android SDK)

#### Label editor support

P-touch Editor (Windows/Mac) Add-In for Microsoft Word/ Excel/Outlook iPrint&Label (iOS/Android)

#### **SDK** availability

(visit http://www.brother.eu/developer)

b-PAC (for Windows) iOS SDK Android SDK

# Supported printer commands

ESC/P P-touch template Raster

## Template update by FTP transfer

Yes

#### Label crop and print

(convert A4 sheets of labels to individual labels automatically)

Yes (Windows only)

#### Barcode symbologies

(using P-touch Editor for Windows)

CODE39, CODE128, UCC/ EAN128 (GS1-128), ITF(I-2/5), CODABAR(NW-7), UPC-A, UPC-E, EAN13, EAN8, ISBN-2 (EAN13 AddOn2), ISBN-5 (EAN13 AddOn5), Laser Barcode, POSTNET, RSS (RSS14 Standard, RSS14 Truncated, RSS14 Stacked, RSS14 Stacked Omni, RSS Limited, RSS Expanded, RSS Expanded Stacked), PDF417 (Standard, Truncate, Micro), QR code (Model1, Model2, Micro), Data Matrix (ECC Square, ECC Rectangular), MaxiCode (Model2, Model3, Model4, Model5), IMB

#### **Barcode symbologies**

(using P-touch Editor for Mac)

CODE39, CODE128, UCC/ EAN128(GS1-128), ITF(I-2/5), CODABAR(NW-7), UPC-A, UPC-E, EAN13, EAN8, ISBN-2 (EAN13 AddOn2), ISBN-5 (EAN13 AddOn5), Laser Barcode, POSTNET, GS1 DataBar (RSS) (GS1 DataBar Omnidirectional, GS1 DataBar Truncated, GS1 DataBar Stacked. GS1 DataBar Stacked Omnidirectional, GS1 DataBar Limited, GS1 DataBar Expanded, GS1 DataBar Expanded Stacked), PDF417 (Standard, Truncate, Micro), QR code (Model1, Model2, Micro), Data Matrix (ECC Square, ECC Rectangular), MaxiCode (Model2, Model3, Model4, Model5), IMB

#### **Barcode symbologies**

(Built-in printer firmware)

CODE39, CODE128, UCC/ EAN-128 (GS1-128), ITF(I-2/5), CODABAR (NW-7), UPC-A, UPC-E, EAN13 (JAN13), EAN8, GS1 DataBar (RSS)(GS1 DataBar Omnidirectional, GS1 DataBar Truncated, GS1 DataBar Stacked. GS1 DataBar Stacked Omnidirectional, GS1 DataBar Limited, GS1 DataBar Expanded, GS1 DataBar Expanded Stacked), PDF417 (Standard, Truncate, Micro), QR Code (Model 1, Model 2, Micro), Data Matrix (ECC200 Square, ECC200 Rectangular), MaxiCode, CODE93, POSTNET, UPC-E EXTENTION

#### Internal fonts

Bitmap fonts: Helsinki, Brussels, Letter Gothic Bold, San Diego, Brougham. Bitmap font sizes: 24 dots, 32 dots, 48 dots. Outline fonts: Helsinki, Brussels, Letter Gothic. Outline font sizes: 33 dots - 400 dots (22 sizes)



#### Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

