





# Compact mono laser printer

**HL-1210W** 





www.brother.eu

## Compact mono laser printer

Perfect for home or small offices. The affordable HL-1210W is fast and compact, offering excellent value for money.

**HL-1210W** 





### **Key Features:**

- 5x toners in the box, each printing 1000 pages
- Compact size
- Wireless connectivity
- 150 sheet paper input
- Up to 20 pages per minute print speed

### **Everything you need for 3 years of printing**\* in one box

In the box with the HL-1210W, you will receive 5 high yield toners, which in total allows you to print 5000 pages\*\*. Not only that, this machine comes with a 3 year warranty as standard – so your printing needs will be covered for the next 3 years.

### Compact and desktop friendly

Whether it's in the home or in your office you can put the compact HL-1210W where it's most convenient for you.

### Built with convenience in mind

Gone are the days of needing endless wires to connect to your printer. With the HL-1210W anyone in your home or office can connect quickly and easily via wireless connection, or alternatively print direct from a mobile or tablet device; you won't even need to turn on a computer.



<sup>\*</sup>Bundle does not include paper.

<sup>\*\*</sup>Print yield is based on 138 pages per month. Yield is declared in accordance with ISO/IEC 19752.

### General

### Technology

Electrophotographic Laser

#### **Processor**

ARM9 200Mhz

### Memory

32MB

### **Wireless Network**

IEEE 802.11b/g/n

### **Control Panel**

LED

### **Local Interface**

Hi-Speed USB 2.0

### **Mobile Print**

Print from your mobile devices to your Brother printer

### Warranty

3 year warranty

### **Print**

### **Print Speed (A4)**

Up to 21PPM (Pages per minute)

#### Resolution

Up to 2400 x 600 dpi (HQ1200 technology)

### **FPOT (First Print Out Time)**

Less than 10 seconds from ready mode and Standard Tray

### Warm Up Time

Less than 18 seconds from sleep mode

### **Print Languages**

GDI

### **Printer Functions**

### N-up Printing<sup>3</sup>

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)

### Manual 2-Sided Print<sup>4</sup>

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

#### Poster Printing<sup>4</sup>

Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages

### Watermark Printing<sup>4</sup>

Watermark your documents with predefined text or with your own user-defined messages

### **Printer Driver**

### Windows

Windows XP Home & Professional, Vista, 7, 8, 8.1 Windows Server 2012, 2012R2, 2008, 2008 R2, 2003, 2003 x64 Edition

### Macintosh<sup>5</sup>

OS X v10.7.5, 10.8.x, 10.9.x

### Linux<sup>5</sup>

CUPS, LPD/LPRng (x86/x64 environment)

\* Windows Server supports network printing only

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19798.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows & Mac® only.

<sup>4</sup> Windows only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

### **Paper Handling**

#### **Paper Input**

Standard Tray - 150 Sheets

#### **Paper Output**

50 sheets Face Down (80g/m2)

### Media Types & Weights Standard Tray

Plain & Recycled paper (between 65 - 105g/m2)

### Media Sizes Manual feed slot

A4, Letter, Legal, Folio,A5,A5(Long Edge),B5,Executive

### Mobile and Web Connectivity

### Brother iPrint&Scan (Android)

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an Android device

### Brother iPrint&Scan (iPad / iPhone / iPod)

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an iPad / iPhone / iPod Touch

### Brother iPrint&Scan (Windows Phone)

Print from and scan to a smart phone running the Windows Phone Operating System

### Brother Print&Scan (Windows 8,10 & RT)

Print from and scan to a Windows 8,10 or Windows RT Tablet

### **Brother Print Service Plugin**

Print from Android devices without a dedicated App

### Fleet Management Tools

### Unattended Installer4

Ability to centrally deploy and customise our drivers and software

### MSI Installer4

Modular installers that can be distributed through Active Directory®

### **BRAdmin Light**<sup>4&5</sup>

LAN/WAN management software

#### **Embedded Web Server**

Web based print management software embedded onto the device

### **Driver Deployment Wizard<sup>4</sup>**

Easily create print drivers for hassle free deployment over your network

### PrintSmart Cost Control

Monitor and control printing costs for all Brother and 3rd party devices

For more information on PrintSmart Solutions visit: www.brother.eu

### **Software**

### Brother iPrint&Scan (Windows & Mac)<sup>5</sup>

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from windows or macOS PC

- 1 Approx declared yield value in accordance with ISO/IEC 19798.
- 2 Calculated with 80g/m² paper.
- 3 Windows & Mac® only.
- 4 Windows only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

### **Network and Security**

#### Wireless Network

IIEEE 802.11b/g/n (Infrastructure Mode/Ad-hoc Mode)

### **Wireless Network Security**

WEP 64/128, WPA-PSK (TKIP/ AES), WPA2-PSK (AES), SMTP-AUTH

### Wireless Setup Support WPS, AOSS

### **Wireless Applications**Vertical Pairing

#### IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SN-MPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMP, Web Services (Print)

#### IPv6

NDP, RA, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SN-MPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMPv6, Web Services (Print)

#### **IP Filter**

Restrict which network users can or cannot access the device over the network (IPv4 only)

#### **E-mail Notifications**

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

### Supplies and Accessories

#### **Inbox Toner**

5,000 Pages Black in accordance with ISO / IEC 19752

### Standard Yield Toner (TN-1050)

5 x 1,000 Pages Black in accordance with ISO / IEC 19752

### Drum Unit (DR-1050)

10,000 Pages (1 page / job)

### Dimensions and Weights

### Without Carton (WxDxH)

340 x 238 x 189 mm - 4.6kg

#### With Carton (WxDxH)

430 x 363 x 474 mm - 8.1Kg

### **Duty Cycles**

### **Recommended Monthly**

250 to 1,800 pages monthly print volume

### Maximum Monthly<sup>6</sup>

Up to 10,000 pages monthly print volume

### **Environment**

### **Power Consumption**

Printing - 380w, Ready - 40w, Deep Sleep - 0.7w

### TEC Value

0.7 kWh/Week

### Sound Pressure Level

Printing - 51dB(A), Ready - Inaudible

### Sound Power

Printing - 6.6B(A), Ready - Inaudible, Deep Sleep - Inaudible

- 1 Approx declared yield value in accordance with ISO/IEC 19798.
- 2 Calculated with 80g/m² paper.
- 3 Windows & Mac® only.
- 4 Windows only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.











### Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com

