



Professional Colour Laser Printer

HL-L9470CDN



PRINT

www.brother.eu

Professional Colour Laser Printer

Create advanced workflows and high-quality glossy documents with ease. The high yield inbox toner considerably reduces print spend, together with robust build quality and excellent paper handling options, makes the HL-L9470CDN the ideal print partner for your business.

HL-L9470CDN



Key features:

- Print up to 40 pages per minute
- 2-sided print, up to 40 sides per minute
- 8.76cm Colour Touchscreen LCD
- Near Field Communication (NFC) connectivity
- 1GB internal memory | 8GB External Storage device
- 520 Sheet paper input tray expandable to 2600
- 12,000 pages (BK), 9,000 pages (CMY) inbox toners¹

Simple. Effortless. Intelligent

The HL-L9470CDN comes with Secure Print Plus, Cloud Secure Print, and Barcode Print Plus as standard, you can securely print and automate workflows straight away. Further integrate your device with leading 3rd party print management and document capture software to create a seamlessly integrated print, capture and output management process.

Flexibility that saves money

There are a range of premium finishing options which you can add to the HL-L9470CDN for optimal efficiency. Whether you need a mailbox to sort your printed documents or a staple finisher to automatically staple your documents, your printer can be easily transformed to help improve business productivity. Boost paper capacity with a choice of additional paper trays, transforming your HL-L9470CDN to a floor-standing device.

Secure by design

As working conditions change, security is more critical than ever. The HL-L9470CDN comes with enterprise level security, giving you peace of mind from the start. You can further protect your device by setting up user authentication, whereby access to certain settings and functions is only given to authorised users or groups.

When quality and performance work together

Straight out of the box comes the exceptionally high yield inbox toners, printing up to 12,000 pages in black and 9,000 pages in colour, so you can start printing without delay. The robust design and long-life components provides confidence that your device will keep on printing.

Contract printing that looks after itself

Let us take care of the day-to-day management of your print infrastructure with managed print services. We help you get the most out of the HL-L9470CDN, ensuring it is setup to your exacting needs and helping manage print costs from the very first page printed.

Solutions enabled

Print secure documents with ease

Secure Print Plus enables you to print your business documents securely and integrates seamlessly with the inbuilt card reader for a low touch print job release solution. Your sensitive documents are only printed when you're ready to collect from the printer. Only authorised staff can collect their documents.

Cloud Secure Print is a convenient built-in feature for printing documents and photos. Remotely submit the print request via email attached documents to a Brother device with an active Internet connection and securely retrieve print jobs via destination device control panel using a senders own unique password protection.

Print barcode fonts from your device

Barcode Print Plus extends printer language intelligence with enhanced support for barcodes standards. Using a software with built-in barcode generation, quickly and accurately add 1D and 2D barcodes to printed document outputs.



Unlock new possibilities with a range of business solutions

Whether you already use print software or would like to understand how specialist print software can help your business, we are here to help.

As a Brother customer, you will have access to a wide choice of leading software vendors including Kofax, YSoft and many more.

We work closely with our software partners across print management and document capture to integrate solutions to transform your workflows. When we partner with a software vendor, we ensure your HL-L9470CDN works even harder to meet your needs.

General

Technology

Electrophotographic Laser

Laser Classification

Class 1 Laser Product

Memory

1GB internal

8GB External Storage device

Control panel

8.76cm Colour

Touchscreen LCD

Local interface¹⁷

Hi-Speed USB 2.0, USB 2.0
Host (Front | Rear)

Wired Network interface

GigE (10Base-T/100Base-
TX/1000Base-T)

Mobile Print

Print from a mobile device to
your Brother printer

Wireless Network interface¹⁶

2.4GHz: IEEE 802.11b/g/n

5GHz: IEEE 802.11a/n

(Infrastructure Mode),

Vertical Pairing

Wi-Fi Direct™

Print wirelessly¹⁶ without having
to use a wireless access point
(both automatic and manual
methods supported)

Print

Print Speed⁸ (A4)

Up to 40ppm (pages per minute)

Print Speed⁸ 2-Sided (A4)

Up to 40 sides per minute
(20 sheets per minute)

Resolution

2,400dpi (2,400 x 600dpi),

600 x 600dpi

FPOT⁹

(First Print out Time)

Less than 10 seconds from
ready mode and standard tray

Warm up time

Less than 20 seconds from
sleep mode

Print languages

PCL5e, PCL5c, PCL6,
(PCL XL Class3.0), BR-Script3,
PDF Version 1.7, XPS Version 1.0

Embedded Fonts (PCL)

73 scalable fonts,
12 bitmap fonts

Embedded Fonts (Postscript)

66 scalable fonts

Embedded Barcodes (PCL)

16 bar codes fonts - Code39,
Interleaved 2 of 5, FIM
(US-PostNet), Post Net
(US-PostNet), EAN-8, EAN-
13, UPC-A, UPC-E, Codabar,
ISBN(EAN), ISBN(UPC-E),
Code128 (set A,B, C),
EAN128 (set A,B,C), Code93,
GS1Databar, MSI

Barcode Print Plus

Complies to industry
standards to easily print from
a comprehensive collection
of the most popular 1D and
2D barcode fonts including
CODABAR, Code 128 A, B, C,
Code 128 with Auto-Switch,
Code 25 Interleaved, Code 39,
Code 39 + Chk Encode Space
Before Data, Code 39 + Mod
43Chk, Code 39 Encode Space
Before Data, Code 93, Code
93 Extended, EAN/JAN-13,
EAN/JAN-13 +2, EAN/JAN-13
+5, EAN/JAN-8, EAN/JAN-8
+2, EAN/JAN-8 +5, GS1-128
(UCC/EAN 128), GS1 DataBar
Standard, Limited, Expanded,
Truncated, and Stacked,
Interleave 25 + Chk, MSI Plessey
+ Chk 10 and Chk 11, PDF-417
and Macro PDF-417, QR Code,
QR Code Model 1 and Model
2, Swiss QR Code, UPC-A,
UPC-A +2, and UPC-A +5,
UPC-E (UPC-E0 and UPC-E1),
UPC-E +2 and UPC-E +5, ZIP+4
PostNet 11, PostNet 9 and
PostNet 5

Printer Functions

N-up Printing³

Reduce up to 2, 4, 9 or 16 or 25 A4 pages into just one A4 page Mac (Airprint) up to 2, 4, 6, 9, or 16

Booklet Printing

Print documents in A5 booklet format using automatic or manual 2-sided print

Poster Printing⁴

Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages

Watermark Printing⁴

Watermark your documents with predefined or user-defined text

Print Profiles³

Store your favourite driver settings as profiles to easily recall them

Print text in black⁴

Converts all text in your documents to black when printed

Direct Print

Print directly from a USB flash memory drive. Supported formats include; PDF 1.7, JPEG, Exif+JPEG, PRN (created using printer driver of model), TIFF (scanned using brother model), XPS version 1.0

Manual 2-Sided Print⁴

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

ID Printing⁴

Add identification to your printed documents (date & time, short custom message or PC username)

Storage Print

Easily retrieve and print your documents all of which are AES 256 encrypted and held within an attached USB Flash memory storage drive (included)

Reverse Print⁴

Rotate the content of a printed document by 180°

Carbon Copy⁴

Prints additional copies of the same document to paper taken from additional paper trays

Print Complete Notice

A printing notification can be set to go to your computer when printing

Match Media⁴

Assign an ID to a specific tray to make the selection of different media types from a specific tray easier

Skip Tray¹⁹

Configures your paper tray selection to avoid specific trays/media for regular printing

Job Separation¹⁹

Insert a different coloured piece of paper between different print jobs to separate them for easy identification.

Secure Print⁴

Protect print jobs with a 4 digit release code required at the device in order for them to be printed

Printer Driver⁵

Windows¹⁸

Windows 10
(Home|Pro|Education|Enterprise)
(32 or 64 bit editions)
Windows 8.1
(32 or 64 bit editions)
Windows 7 SP1
(32 or 64 bit editions)
Windows Server
2019, 2016, 2012R2,
2012, 2008R2
Windows Server 2008 SP2
(32 & 64 bit editions)

Macintosh²¹

macOS 10.14.x or greater

Linux

CUPS, LPD/LPRng
(x86/x64 environment)

PCL Driver

Generic PCL XL driver

PostScript Universal Printer Driver

Driver for Windows that enables you to print to any network or locally connected Brother laser printer that supports PostScript

Paper Handling

Paper Input²

Standard (Tray 1) - 520 Sheets

Multi Purpose Tray -
100 Sheets, 15 Envelopes

Paper Output²

250 sheets face down
1 sheet face up (straight path)

Media Sizes

Standard (Tray 1)

Letter, Legal, Executive, A4, A5, A5 (Long Edge), A6, B5(ISO), Mexico Legal, India Legal, Folio, 16K (195 x 270mm)

Multi Purpose Tray

Width: 76.2mm - 215.9mm
Length: 127mm - 355.6mm
Envelopes; C5, Com-10, DL, Monarch

Optional (Trays 2-5)

Letter, Legal, Executive, A4, A5, Mexico Legal, India Legal, Folio, 16K (195 x 270mm)

2-Sided Print

A4, Letter, Legal, Mexico Legal, India Legal, Folio
(Desired paper size can be selected manually)

Media Types

Standard (Tray 1)

Thin Paper, Plain Paper, Thick Paper, Thicker Paper, Recycled Paper

Multi Purpose Tray

Thin Paper, Plain Paper, Thick Paper, Thicker Paper, Recycled Paper, Bond Paper, Label, Envelope, Env. Thin, Env. Thick, Glossy Paper²⁰

Optional (Trays 2-5)

Thin Paper, Plain Paper, Thick Paper, Recycled Paper

2-Sided Print

Thin Paper, Plain Paper, Thick Paper, Thicker Paper, Recycled Paper, Glossy paper

Media Weights

Standard (Tray 1),

Multi Purpose Tray -

60 - 230gsm

Optional (Trays 2-5) -

64 - 105gsm

Optional Stacker/Stapler

60 - 200gsm (with offset)

60 - 90gsm (with Staple)

Paper Input / Output Sensors

Onscreen and optional email alert notifications when input trays are empty or running low or the output stack is full.

Mobile and Web Connectivity

Apple AirPrint

Print most common file types from any AirPrint enabled application

Brother Print Service Plugin⁵

Print from Android devices without a dedicated App

Mopria

Print most common file types from Mopria supported Android devices

Web Connect^{10, 15}

Without using a PC, download and print from Box, SharePoint Online, Dropbox, Evernote, OneDrive, Google Drive™, OneNote

Fleet Management Tools⁵

Unattended Installer⁴

Ability to centrally deploy and customise our drivers and software

MSI Installer⁴

Modular installers that can be distributed through Active Directory®

BRAdmin⁴

LAN/WAN management software

Embedded Web Server

Using the IP address or node name of your device, access via a web browser the web based print management software embedded onto the device using an encrypted password

Driver Deployment Wizard⁴

Easily create print drivers for hassle free deployment over your network

Mass Deployment Tool⁴

Provides a configuration interface to help manage and deploy device settings

Status Monitor⁴

Monitor the status of your machine from your computer

Software⁵

Brother iPrint&Scan

Print and check the machine status from windows or macOS PC

Brother Utilities

Provides setup guides, manual⁵, FAQ & troubleshooting and contact to Brother customer service

Easy Setup²²

Simplifying the install process with easy access to the right drivers and software for the installation of your Brother machine for your PC

Network Security

Wired Network Security

SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP), SNMP v3, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, Ipsec

IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/v3, ICMP, Web Services (Print), CIFS client, SNTTP client, LDAP

IPv6

NDP, RA, DNS resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/v3, ICMPv6, Web Services (Print), CIFS Client, SNTTP Client, LDAP

IP Filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

Wireless Network Security^{11, 16}

WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP), SNMP v3, 802.1x (EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec

Wireless Setup Support¹⁶

Wi-Fi Protected Setup (WPS)

Display IP Address

The dynamic IP assigned to your device can be displayed on the home screen

Security Features

E-mail Notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

E-mail Reports

Receive usage reports on a regular basis via e-mail

Automatic Intrusion Detection

All Brother Print devices are secure by design. Devices automatically recognise security attacks and take preventative measures, including rebooting where necessary, in order to ensure the device remains secure.

Digitally-signed Firmware

The firmware for Brother Print devices is digitally signed and secure

Active Directory/LDAP Authentication

Utilise existing infrastructure to restrict access to Brother devices using AD/LDAP. staff can easily use their existing network login credentials to authenticate

Port-based Network Access Control

(IEEE 802.1x)
Brother devices are in full compliance with this standard, to allow connection to an 802.1x EAP (Extensible Authentication Protocol) protected network

Restrict network protocols

The Protocol Control feature allows an administrator to restrict communication protocols (e.g. FTP, Telnet) as required

Setting Lock

Secures access to the devices control panel by locking it

Secure Function Lock 3.0

Use a 4 digit pin or a password to identify and authenticate an individual or groups of users over a network. Allows access control with username for up to 200 users

Cloud Secure Print¹⁰

Enables password protected driverless print job release

Store Print Log

Allows the audit of a print log file saved to CIFS server. Record ID, type, name, user, date, time, page count for every print job

Firmware Updates

In addition to allowing automatic updates to the latest version the printer can be set to not receive older firmware versions to avoid downgrade by unauthorised user

SysLog

Allows IT Admin to access a single application (SIEM tool) to get device status updates for audit purposes over Syslog

Near-Field Communications (NFC) / Card Reader Support

Integrated NFC Reader

Supported NFC standards include: (ISO14443 Type A) MIFARE Standard/Plus/Ultralight/Ultralight C/DESfire my-d move, Tag-it (ISO15693 Type B)

External NFC Card Reader Support

RFIDeas pcProx Enroll

- RDR-6081AKU
- RDR-6281AKU
- RDR-6381AKU
- RDR-6E81AKU
- RDR-6H81AKU

RFIDeas AIR ID Enroll

- RDR-7081AKU
- RDR-7581AKU
- RDR-7F81AKU

Elatec

- TWN3 MIFARE
- TWN3 MIFARE NFC
- TWN3 Multi ISO
- TWN4 MIFARE NFC

(3rd party card readers require additional purchase. Other card readers supported if registered via the embedded web server)

Solutions

Barcode Print Plus

Easily print industry standard barcodes from your Brother printer

Secure Print Plus²¹

Using the NFC card reader allows print jobs to be released by the authenticated user, making sure confidential data doesn't fall into the wrong hands

Developers

Brother Solutions Interface (BSI)

Create powerful cloud and on premise solutions directly integrating the advanced print, scan and security capabilities of Brother devices.

For more information visit:

www.brother.eu/developers

Supplies¹, Upgrades and Accessories

Inbox Toner

1 x 12,000 pages (BK)
3 x 9,000 pages (CMY)

High Yield Toner

TN821XL
1 x 12,000 pages (BK)
3 x 9,000 pages (CMY)

Super High Yield Toner

TN821XXL
1 x 15,000 pages (BK)
3 x 12,000 pages (CMY)

Drum Unit (DR821CL)

Approx 100,000 pages at
3 pages per job
Approx 30,000 pages at
1 page per job

Belt (BU800CL)

Approx. 100,000 pages at
1 page per job
Approx. 150,000 pages at
2 pages per job

Waste Toner Box (WT800CL)

Approx 100,000 pages
2 pages per job

Carton Contents

Machine, Inbox Toners, Drum,
Belt, Waste Toner Box, Power
Supply Cord, Quick Set-Up
Guide, Warranty Card
(PC interface cable NOT
included)

Optional Card Reader Holder

(CH-1000)
External NFC Card reader holder

Optional Filter Holder

(FH-3000)
Used in Quiet Mode
(Germany Only)

Optional Wi-Fi Module

(NC-9000w)

Optional Paper Trays²

250 sheet tray (LT-330CL)
500 sheet tray (LT-340CL)
4 x 520 sheet tower tray
(TT-4000)
Tower Tray Connector
(TC-4100)
Maximum combinations of 3
LT-330CL or 2 LT-340CL,
1 x LT-330CL or 1 x LT-340CL
together with TT-4000 and
TC-4100

Finishing Options² Mailbox (MX-4000)

100 sheets x 4 bins, convertible
to 400 sheets x 2 bins

Stapler Finisher (SF-4000)⁴

500 Sheets (face down) Stapler
Finisher with 1,950 staple starter
cartridge

Staple Supply (SR100)

2 cartridges 5,000 staples each

Dimensions and weights

Printer without Carton (WxDxH)

442 x 541 x 403mm - 29.4kg

Printer with Carton (WxDxH)

557 x 628.2 x 633.5mm -
34.7kg

Optional Mailbox (WxDxH)

367 x 416 x 381mm

Optional Card Reader Holder (WxDxH)

External: 83 x 62 x 111.5mm
Internal: 60 x 90mm - 0.1Kg

Optional Filter Holder (WxDxH)

External: 308 x 126 x 68mm
Internal: 117 x 51 x 293mm -
0.2Kg

Optional Paper Trays (WxDxH)

250 sheet tray:
410 x 486 x 97mm - 5.1Kg
500 sheet tray:
410 x 486 x 133mm - 6.6Kg
4 x 520 sheet tower tray:
660 x 660 x 717.4mm - 46.6Kg
Tower Tray Connector:
444 x 486 x 103mm - 5.9Kg

Finishing Options (WxDxH)

4 bin Mailbox:
367 x 416 x 381mm - 4.4Kg
500 Sheet Stapler Finisher:
410 x 478.5 x 347.5 mm -
7.8Kg

Duty Cycle

Recommended Monthly

Up to 15,000 pages monthly
print volume

Maximum Monthly⁶

Up to 150,000 pages monthly
print volume

Environment

Power Requirement

220-240V
AC 50/60Hz

Power Consumption¹²

Printing - 770W
(420W in quiet mode)
Ready 85W
Sleep 15.6W
Deep Sleep 1W
Power Off 0.04W

Sound Pressure¹³

Printing 56.5dbA
Ready 17.2dbA
Quiet Mode 53dbA

Sound Power¹⁴

Printing 6.88BA
Ready 3.02BA
Quiet Mode 6.68BA

TEC Value

0.662kWh / Week

Operating Environment

Humidity 20 - 80%
10°C - 32°C
50°F - 90°F

Storage Environment

Humidity 10 - 90%
0°C - 40°C
32°F - 104°F

Disk Space Requirements

50MB - Windows Drivers Only
1.6GB - Windows 10, 8.1, 7
All applications inc Drivers
macOS - 500MB All applications

- 1 Approx declared toner yield value in accordance with ISO/IEC 19798
- 2 Calculated with 80gsm sheets of paper
- 3 Windows & macOS
- 4 Windows only
- 5 Free download from the Brother Solutions Centre <http://solutions.brother.com>
- 6 Number of printed pages per month can be used to compare designed durability between Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that exceeds your print requirements
- 7 Requires Brother Software
- 8 Based on ISO/IEC 24734
- 9 Based on ISO/IEC 17629
- 10 Requires an Internet connection
- 11 Wi-Fi Direct supports WPA2-PSK (AES) only
- 12 All values are approximate; power consumption varies depending on the usage environment or part wear
- 13 Based on ISO 7779
- 14 Based on RAL-UZ171
- 15 Requires additional activation
- 16 Optional Wireless module required, 5Ghz may not be available in your region
- 17 Third Party USB hubs not supported
- 18 Win7 / Server2008 SP2/R2 Extended Security Update (ESU) legacy support until 10/01/2023
- 19 Requires installation of optional trays
- 20 Set only a single sheet
- 21 On macOS AirPrint only
- 22 For more information visit <http://setup.brother.com>



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.
www.brotherearth.com

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

brother
at your side